

# PRODUCT INFORMATION SHEET


Actual status: 15.02.18



## RELAY BOARD 8 X

RB 8

Part-No.: 30077



Control board for the connection of up to 8 additional external changeover contacts for the fire control panels detect 3004plus

- Possibility for 8 additional change over contacts for the control of external circuits of up to 250 V/5A
- 8 low-active inputs for the parallel switch of the outputs of the control board
- 1 input for the release or the switch off of the functions of the control board (e.g. at „FCP - door open“)
- Power supply 24 V via power supply unit of the fire control panel
- Modular housing for the easy mounting onto a DIN rail
- 8 LEDs to indicate the status of the outputs

### Technical Data

Supply Voltage	21 V to 28 V DC
Quiescent Current	5 mA
Alarm Current	30 mA to 240 mA (30 mA per relay)
Output	8 changeover 250 V/5 A
Ambient temperature	-10°C to +50°C
Humidity	10 % to 85 % (not condensing)
Dimensions (H x B x T)	125 mm x 110 mm x 60 mm
Weight	appr. 300 g
Material	ABS, Glass
Colour	green